

# **MICROWAVE LEVEL SWITCH**

# MICROWAVE LEVEL SWITCH






MICROWAVE TRANSMITTER
AND RECEIVER SENSORS

This range of Microwave level switches provides a simple non-contact, non-intrusive option suitable for many applications on powders and solids. An installation comprises of a transmitter and a receiver which are mounted facing one another at distances up to a maximum of 40m apart.

During operation the transmitter emits a continuous, low power, microwave beam to the receiver and an output relay is energised or de-energised when this beam is obstructed by the material being monitored . The switch trigger point is determined by the amount of microwave energy received and can therefore be adjusted to cater for different products and different sensitivity settings depending upon the application.

Typical applications for detecting presence and non-presence of materials include flow and no flow conditions, point level detection, blocked chute detection and also proximity switch detection for reversing vehicles such as quarry trucks and rail cars.



19

PB

# **MICROWAVE FEATURES**

#### NON CONTACT PRINCIPLE

The switches can be installed behind various window materials such as Teflon or Polypropylene to maintain the integrity of the vessel or chute even if they need to be removed.

## HIGH PENETRATION AND SURFACE COATING IMMUNITY

The microwaves easily penetrate any surface contaminants which makes the switches ideal for applications with high build up on the tank or silo walls. This switch is also immune to problems with airborne contaminants such as dust or steam.



A wide beam angle on the transmitter sensor enables alignment to be carried out easily for the two sensors. The received power level is also clearly indicated by a bank of 15 LEDs which enable clear visual indication of the state of power received and the location of the switch set point (see opposite).



This device requires no special procedures for its operation and use as power limitations are well below any required industry standards.

## NEW HETERODYNE DETECTION PRINCIPLE

Many older microwave switches employ a diode detection technology but this new range uses the Heterodyne detection principle which has the ability to obtain a proportional output to the power received. This enables the switch to increase its operating range and penetrability without having to increase the power of the transmitted microwave signal.



A wide range of flanges and a standard 1" BSPP process thread make this range extremely easy to retrofit to new and old installations utilising existing process connections.




**CYCLONE** 

LEVEL SWITCHES

# **ADVANTAGES AND BENEFITS**


- Non-contact technology with no moving parts reduces maintenance costs
- Versatile technology for liquids, slurries, solids, pellets and powders
- Long measuring range up to 40m with adjustable sensitivity to suit most applications
- Simple to install and commission leading to reduced installation costs
- Immune to coatings on tank walls improving reliability and reduces maintenance costs
- Non-invasive technology, with no long probes to insert, internal product build up is reduced
- Suitable for demanding environments such as corrosive, high dust, high vibration or vapours
- Chemical resistant window options for corrosive applications




# **MICROWAVE LEVEL SWITCH**

## SIMPLE COMMISSIONING WITH LED ADJUSTMENT

The sensitivity is adjusted visually using the 15 LED indicator array. The received power level and sensitivity set-point are indicated on the receiver by a bank of 15 LEDs. The received power is clearly indicated by the brightest LED. Then, by a simple adjustment screw, the relay set point (dimmer LED) can be adjusted either way. This system allows for a very clear visual sensitivity adjustment and greatly simplifies maintenance and commissioning as the switch positions and sensitivity are seen at a glance.





## HIGH VIBRATION & HAZARDOUS APPLICATIONS USE ISOLATED, NON-INVASIVE MOUNTING


Sensors may be protected from high temperatures, hazardous materials, vibration and shock by providing detecting windows through which the microwaves can pass.

Detecting windows should be made of non-metallic materials such as ceramic, glass, teflon or polypropylene. With these materials there is minimal loss of microwave energy between the two sensors.

The detecting windows should be at least 60mm in diameter as microwaves pass more easily through larger apertures. The distance between the window and the sensing face should be less than 200mm.


## **MOUNTING OPTIONS**

**STANDARD** 




Standard 1" BSPP process connection directly into the tank socket. Suitable for low abrasion applications.

**FLANGE** 



Flange with 1" BSPP process connection through a flange socket with Teflon window. The angle of the tank wall will have little or no effect on the transmitter.

FLANGE WITH INSERT



Flange process connection with optional polypropylene plug sandwiched between flanges but flush with tank wall. This provides additional sensor protection.

## PPLICATIONS FOR ALL INDUSTRIES







WATER & WASTE



**PROCESS** 





**CHEMICAL** MINING

# **SPECIFICATION**

#### **Model reference**

Transmitter : HYC-MWS-ST-2-24V Receiver : HYC-MWS-SR-2-24V

## **Power supply**

Transmitter : 24VDC ±10% Receiver : 24VDC ±10%

## **Power consumption**

Transmitter : 1W, 42mA Receiver : 2W, 83mA

## **Operating Range**

Maximium 40 metre

(Note: Operating distance may vary depending upon installation).

## Frequency & transmission power

Approx. 24GHz, less than 100mW (E.I.R.P.)

## Received power level

Indicated by 1 of 15 LED indicators Note: Indicator is fully illuminated

## Sensitivity-set-point

Indicated by 1 of 15 LED indicators Note: Indicator is half illuminated

#### Beam angle

Approx. 20 degrees (inclusive angle)

## **Relay contact**

1C (SPDT) relay contact 30VDC, 2A

## **Response time**

10msec.

## Adjustable time delay

0.1 ~ 10sec. adjustable

## Delay time from power on to function

Transmitter : Approx. 50msec. Receiver : Approx. 5sec

#### **Operating ambient temperature**

-10°C~+55°C

## Option:

Ceramic high temperature extension (300mm)

-50°C ~+600°C. EK version

## Storage ambient temperature

-20°C~+70°C

## **Continuous maximum pressure**

5 bar (75psi)

## **Enclosure rating**

IP65 protection

## **Enclosure construction**

Diecast aluminum

## Weight


Transmitter : 1kg Receiver : 1kg

## **CE Certification Standards**

EN300440-2 EN301489-1/3

In accordance with: R&TTE Directive


**EMC Directive** 



# **HYCONTROL LEVEL TECHNOLOGIES**

## **Product Range For Solids:-**

- (1) TDR Radar For Solids
- (2) Ultrasonic, 'Through Air'
- (2) 2 Wire Ultrasonic Transmitter
- (3) FMCW 2 Wire Radar
- (4) Continuous 'Servo' Level Indicator
- (5) FMCW 2 Wire Radar
- (6) Capacitance Level Switch
- (7) Vibrating Probe Level Switch
- (8) Rotating Paddle Level switch
- (9) Microwave Level Switch
- (10) Doppler Flow Switch



# **Product Range For Liquids :-**

- (1) By-Pass Level Indicator With Radar
- (2) TDR Radar For Liquids
- (3) 2 Wire Ultrasonic Transmitter
- (4) FMCW 'Horn' Radar 2 Wire
- (5) Magnetic Float Switches
- (6) FMCW 2 Wire Radar
- (7) Capacitance Level Switch
- (8) RF Admittance Level Switch
- (9) Side Mounting 316 SS Float Switch
- (10) Tuning Fork Level Switch
- (11) Tuning Fork Level Switch
- (12) Ultrasonics 'Through Wall'
- (13) Mini Magnetic Float Level Switch

